

UHF CHANNEL ASSIGNMENT

CURRENT VHF CHANNEL ASSIGNMENT

TK-3130 2CH	TK-3130 Preset Table Number	TK-3200P Series			TK-3200P Preset Table Number	Preset Table Frequency (MHz)	NOTE
		2CH	8CH	UHF 15CH			
				0	OFF	67.0	
	1 (Brown)			9	464.5000	67.0	N/W
1	2 (Yellow)	1	1	2	464.5500	67.0	N/W
	3 (J)			10	467.7625	67.0	N
	4 (K)			11	467.8125	67.0	N
	5 (Silver Star)			12	467.8500	67.0	N/W
	6 (Golg Star)			13	467.8750	67.0	N/W
	7 (Red Star)			14	467.9000	67.0	N/W
2	8 (Blue Star)	2	2	8	467.9250	67.0	N/W
			3	3	461.0375	67.0	N
			4	4	461.0625	67.0	N
			5	5	461.0875	67.0	N
			6	6	461.1125	67.0	N
			7	7	461.1375	67.0	N
			8	8	461.1625	67.0	N
				15	461.1875	67.0	N
				16	461.2125	67.0	N
				17	461.2375	67.0	N
				18	461.2625	67.0	N
				19	461.2875	67.0	N
				20	461.3125	67.0	N
				21	461.3375	67.0	N
				22	461.3625	67.0	N
				23	462.7625	67.0	N
				24	462.7875	67.0	N
				25	462.8125	67.0	N
				26	462.8375	67.0	N
				27	462.8625	67.0	N
				28	462.8875	67.0	N
				29	462.9125	67.0	N
				30	464.4875	67.0	N
				31	464.5125	67.0	N
				32	464.5375	67.0	N
				33	464.5625	67.0	N
				34	466.0375	67.0	N
				35	466.0625	67.0	N
				36	466.0875	67.0	N
				37	466.1125	67.0	N
				38	466.1375	67.0	N
				39	466.1625	67.0	N
				40	466.1875	67.0	N
				41	466.2125	67.0	N
				42	466.2375	67.0	N
				43	466.2625	67.0	N
				44	466.2875	67.0	N
				45	466.3125	67.0	N
				46	466.3375	67.0	N
				47	466.3625	67.0	N
				48	467.7875	67.0	N
				49	467.8375	67.0	N
				50	467.8625	67.0	N
				51	467.8875	67.0	N
				52	467.9125	67.0	N
				53	469.4875	67.0	N
				54	469.5125	67.0	N
				55	469.5375	67.0	N
				56	469.5625	67.0	N

TK-2200P 2CH	TK-2200P 8CH	TK-2200P Preset Table Number	Preset Table Frequency (MHz)	QT	NOTE
		1	151.6250	67.0	N
		2	151.9550	67.0	N
1	1	3	154.5700	67.0	N
2	2	4	154.6000	67.0	N
		5	151.7000	67.0	N
		6	151.7600	67.0	N
		7	151.8200	67.0	N/W
		8	151.8800	67.0	N/W
		9	151.9400	67.0	N/W
	8	10	151.5125	67.0	N
		11	151.6550	67.0	N
		12	151.6850	67.0	N
		13	151.7150	67.0	N
		14	151.7450	67.0	N
		15	151.7750	67.0	N
		16	151.8650	67.0	N
		17	151.8950	67.0	N
		18	151.9250	67.0	N
		19	152.7000	67.0	N
		20	154.4900	67.0	N
		21	154.5150	67.0	N
		22	154.5275	67.0	N
		23	154.5400	67.0	N
		24	154.6000	67.0	N
		25	154.6550	67.0	N
		26	158.4000	67.0	N
		27	158.4075	67.0	N

MURS

MOTOROLA RD 2CH	MOTOROLA RD 8CH	RD Preset Table Number	Preset Table Frequency (MHz)	QT	NOTE
		1	151.6250	67.0	W
		2	151.9550	67.0	W
		3	152.8850	67.0	W
		4	152.9150	67.0	W
		5	151.7000	67.0	N
		6	151.7600	67.0	N
		7	152.9450	67.0	N/W
		8	151.8350	67.0	N/W
		9	151.8050	67.0	N/W
		10	151.5125	67.0	N
		11	151.6550	67.0	W
		12	151.6850	67.0	W
		13	151.7150	67.0	W
		14	151.7450	67.0	W
		15	151.7750	67.0	W
		16	151.8650	67.0	W
		17	151.8950	67.0	W
		18	151.9250	67.0	W
		19	152.7000	67.0	W
1	1	20	154.4900	67.0	W
2	2	21	154.5150	67.0	W
		22	154.5275	67.0	N
		23	154.5400	67.0	W
		24	154.0050	67.0	W
		25	154.6550	67.0	W
		26	158.4000	67.0	W
	8	27	158.4075	67.0	N

CHANGE
S FROM
XTN

MOTOROLA NEW DEFAULT FREQUENCIES

57	462.1875	67.0	N
58	462.4625	67.0	N
59	462.4875	67.0	N
60	462.5125	67.0	N
61	467.1875	67.0	N
62	467.4625	67.0	N
63	467.4875	67.0	N
64	467.5125	67.0	N
65	451.1875	67.0	N
66	451.2375	67.0	N
67	451.2875	67.0	N
68	451.3375	67.0	N
69	451.4375	67.0	N
70	451.5375	67.0	N
71	451.6375	67.0	N
72	452.3125	67.0	N
73	452.5375	67.0	N
74	452.4125	67.0	N
75	452.5125	67.0	N
76	452.7625	67.0	N
77	452.8625	67.0	N
78	456.1875	67.0	N
79	456.2375	67.0	N
80	456.2875	67.0	N
81	456.3375	67.0	N
82	456.4375	67.0	N
83	456.5375	67.0	N
84	456.6375	67.0	N
85	457.3125	67.0	N
86	457.4125	67.0	N
87	457.5125	67.0	N
88	457.7625	67.0	N
89	457.8625	67.0	N